

PROGRAMMING



1. Apply power (120, 208, or 240 VAC) to the A1 & A2 terminals.
2. Hold down the SET and ADJ buttons for at least 3 seconds.
3. Repeatedly press the ADJ button until the letter E appears on the left-hand side.
4. Press the SET button.
5. Press the ADJ button until the letters M S appear.
6. Press the SET button.
7. Press the ADJ button to adjust the first digit (minutes) to 1.
8. Press the SET button.
9. Press the ADJ button to adjust the second digit (tens of seconds) to 3.
10. Press the SET button.
11. Press the ADJ button to adjust the third digit (seconds) to 0.
12. Press the SET button.
13. Press the ADJ button so there is an arrow facing downward.
14. Press the SET button.

TESTING

STEP	ACTION	RESULT
1.	Apply power (120, 208, or 240 VAC) to the A1 & A2 terminals.	Idle state.
2.	Make control signal connection at B1. No control signal is applied.	Remains in idle state.
3.	Apply control signal (logic high).	Relay closes (ports 15-18).
4.	Remove control signal (logic low).	Relay remains closed for 1.5 minutes.

NOTICE In Step 4, if control signal is reapplied while the relay is still closed, Step 3 will restart.